

TITLE OF THE INVENTION

COMMUNICATION APPARATUS HAVING WIRED COMMUNICATION FUNCTION  
AND WIRELESS COMMUNICATION FUNCTION,

5 AND CONTROL METHOD THEREFOR

BACKGROUND OF THE INVENTION

Field of the Invention

10 The present invention relates to communication  
apparatuses having a wired communication function and a  
wireless communication function, and to control methods  
therefor.

Description of the Related Art

15 Recently, wireless switching systems for establishing a  
wireless link between a facsimile apparatus and a wireless  
switchboard have been installed as local communication  
systems in offices and the like.

20 When only wireless links are established at locations  
in which such wireless switching systems are used, it is not  
possible to use facsimile apparatuses which cannot perform  
wireless communication.

25 Japanese Patent Laid-Open No. 2000-174922 describes a  
communication apparatus having a wireless communication  
function and a wired communication function, in which

switching between the wireless communication function and the wired communication function is performed by manual setting by a user.

When moving the above communication apparatus from a place in which only wired connections are used to a place in which only wireless links are used, the user is required to change the setting from a wired communication mode to a wireless communication mode.

It is also necessary to provide hardware such as a communication mode setting switch.

When moving the above communication apparatus from a place in which only wireless links are used to a place in which only wired connections are used, the user is required to change the setting of the communication mode.

#### SUMMARY OF THE INVENTION

Accordingly, it is an object of the present invention to enable a communication apparatus to perform communication in accordance with the environment in which the communication apparatus is installed.

Another object of the present invention is to automatically switch between wireless communication and wired communication in accordance with the environment in which the communication apparatus is installed.

According to an aspect of the present invention, a communication apparatus having a wired communication function and a wireless communication function is provided that includes a determining unit for determining whether connection is made to a wired communication line, and a control unit for selectively controlling, in accordance with the determination by the determining unit, whether to transmit data from the communication apparatus through one of the wired communication line and a wireless communication link.

According to another aspect of the present invention, a communication apparatus having a first mode for performing wireless communication under the control of a first wireless communication apparatus and a second mode for controlling so that a second wireless communication apparatus performs wireless communication is provided. The communication apparatus includes a determining unit for determining whether connection is made to a wired communication line, and a control unit for controlling, in accordance with the determination by the determining unit, so as to switch between the first mode and the second mode.

According to a further aspect of the present invention, a method for controlling a communication apparatus having a wired communication function and a wireless communication function is provided that includes a determining step of

determining whether connection is made to a wired communication line. The method includes a control step of selectively controlling, in accordance with the determination in the determining step, whether to transmit data from the communication apparatus through one of the wired communication line and a wireless communication link.

According to yet a further aspect of the present invention, a method for controlling a communication apparatus having a first mode for performing wireless communication under the control of a first wireless communication apparatus and a second mode for controlling so that a second wireless communication apparatus performs wireless communication is provided. The method includes a determining step of determining whether connection is made to a wired communication line, and a control step of controlling, in accordance with the determination in the determining step, so as to switch between the first mode and the second mode.

Further objects, features, and advantages of the present invention will be apparent from the following description of the preferred embodiments with reference to the attached drawings.

# BRIEF DESCRIPTION OF THE DRAWINGS

Figs. 1A to 1C are respectively block diagrams of the structures of communication systems CS1, CS2, and CS3, which include a facsimile apparatus FS1 according to an embodiment of the present invention;

Fig. 2 is a block diagram of the structure of the facsimile apparatus FS1 of the present embodiment;

Fig. 3 is a block diagram of the internal structure of a Personal Handyphone System (PHS) processor 222 included in the facsimile apparatus FS1 of the present embodiment;

Fig. 4 is a flowchart showing a process for making a call from a PHS 100 when the facsimile apparatus FS1 of the present embodiment is connected to an integrated services digital network (ISDN) 101;

Fig. 5 is a flowchart showing a process for performing facsimile communication by the facsimile apparatus FS1 of the present embodiment when the facsimile apparatus FS1 is connected to the ISDN 101;

Fig. 6 is a flowchart showing a process for performing facsimile communication by the facsimile apparatus FS1 of the present embodiment when the facsimile apparatus FS1 is not connected to the ISDN 101;

Fig. 7 is a sequence diagram of how the facsimile apparatus FS1 of the present embodiment places an outgoing

call when the facsimile apparatus FS1 is connected to the ISDN 101;

Fig. 8 is a sequence diagram of how the facsimile apparatus FS1 of the present embodiment places an outgoing  
5 call when the facsimile apparatus FS1 is not connected to the ISDN 101;

Fig. 9 is a flowchart showing a process for controlling the facsimile apparatus FS1 of the present embodiment; and

Fig. 10 is a flowchart showing a process for controlling the facsimile apparatus FS1 of the present embodiment.

## DESCRIPTION OF THE PREFERRED EMBODIMENTS

### FIRST EMBODIMENT

Figs. 1A to 1C respectively show the structures of communication systems CS1, CS2, and CS3, which include a facsimile apparatus FS1 according to a first embodiment of the present invention.

Fig. 1A shows the structure of the communication system CS1 in which the facsimile apparatus FS1 is connected to an integrated service digital network (ISDN) 101. In the communication system CS1, the facsimile apparatus FS1 is also connected to a destination terminal FS2 through the  
25 ISDN 101.

Fig. 1B shows the structure of the communication system CS2 in which the facsimile apparatus FS1 is not connected to the ISDN 101.

The communication system CS2 includes the facsimile apparatus FS1 and a wireless switchboard RC1. The ISDN 101 and the wireless switchboard RC1 are interconnected, and the ISDN 101 and the destination terminal FS2 are interconnected. A digital wireless link is established between the facsimile apparatus FS1 and the wireless switchboard RC1. In this case, the facsimile apparatus FS1 functions as a remote station of the wireless switchboard RC1. The wireless switchboard RC1 is an example of a second communication apparatus connected to a wired communication line.

Fig. 1C shows the structure of the communication system CS3 in which the facsimile apparatus FS1 is connected to the ISDN 101.

The communication system CS3 includes the facsimile apparatus FS1 and a Personal Handyphone System (PHS) 100, which is an example of a digital cordless phone. The facsimile apparatus FS1 is connected to the destination terminal FS2 through the ISDN 101. In this case, the facsimile apparatus FS1 functions as a master station of the PHS 100.

The PHS 100 transmits and receives data to and from the facsimile apparatus FS1 through a digital wireless link.

The PHS 100, which is a remote station wireless terminal unit, is connected to the ISDN 101 through the facsimile apparatus FS1.

Fig. 2 shows the structure of the facsimile apparatus FS1 of the first embodiment of the present invention.

The facsimile apparatus FS1 includes a central processing unit (CPU) 201, a data bus/address bus 202, a read only memory (ROM) 203, a random access memory (RAM) 204, and a facsimile engine controller 205.

The CPU 201 controls the entire facsimile apparatus FS1 in accordance with a program stored in the ROM 203.

The facsimile engine controller 205 includes a CPU (microcomputer) 206 that performs various controlling operations in accordance with a program stored in a ROM (not shown) and a RAM 207. The facsimile engine controller 205 is connected to a data bus 208.

The facsimile apparatus FS1 includes a shared register 209 that communicates data between a system at the CPU 201 side and a system at the CPU 206 side, a color printer/color scanner 210, an operation panel 211, a facsimile modem 212, a handset 213, a speaker 214, an on-hold melody generator 215, and a display unit 236.

The shared register 209, the color printer/color scanner 210, the operation panel 211, the facsimile modem 212, the handset 213, the speaker 214, the on-hold melody



generator 215, and the display unit 236 are controlled by the facsimile engine controller 205 and are connected to an analog switch 216. Audio data or facsimile analog data is connected to the ISDN 101 through the analog switch 216.

5           The facsimile apparatus FS1 further includes a modular connector 217, a digital service unit (DSU) 218, an ISDN interface part 219, a high-level data link control (HDLC) controller 220, a PHS Internet Access Forum Standard (PIAFS) controller (wireless data communication protocol processor) 221, a PHS processor 222, and a bus selector switch 223.

10           The modular connector 217 interconnects the facsimile apparatus FS1 and the ISDN 101 (U-point).

15           The DSU 218 converts data communicated between a station switchboard of the ISDN 101 and the facsimile apparatus FS1 into a signal at a transistor-transistor logic (TTL) level.

20           The ISDN interface part 219 controls layers 1 to 3 of the ISDN 101 and has a function for inputting/outputting data on the B-channels of the ISDN 101. The ISDN interface part 219 includes a digital phase locked loop (PLL) 235. The digital PLL 235 has a function for generating an 8 KHz clock in synchronism with data received from the ISDN 101.

          The HDLC controller 220 assembles/decomposes data in an HDLC format.

25           The PIAFS controller 221 assembles/decomposes frames in

a wireless data communication protocol format.

The PHS processor 222 performs PHS wireless communication protocol processing, pulse code modulation (PCM) code conversion, and the like.

5 Under the control of the CPU 201, the bus selector switch 223 has a function for connecting data, which is transmitted on B1 channel and B2 channel of the ISDN 101, to either the HDLC controller 220 or the PHS processor 222.

Major signal lines included in the facsimile apparatus FS1 of the first embodiment are described next.

10 A signal line 224 is a serial communication signal line that communicates a control signal between the CPU 201 and the CPU 206. A signal line 225 is a serial communication signal line that communicates a control signal between the CPU 201 and the PHS processor 222.

15 A signal line 226 is a 64-Kbps serial transmission signal line for B1 channel of the ISDN 101, and a signal line 227 is a 64-Kbps serial transmission signal line for B2 channel of the ISDN 101.

20 A signal line 228 is a serial communication signal line input to and output from the HDLC controller 220 and transmits data in the HDLC frame format.

25 Signal lines 229 and 230 are serial communication signal lines which are input to and output from the PHS processor 222 at a line speed of 64 Kbps. The signal lines

229 and 230 are signals that transmit data obtained by converting a 32-Kbps signal transmitted through a digital wireless link into 64-Kbps data or data obtained by converting an analog signal input from the analog switch 216 into 64-Kbps PCM data. When outputting data from the PHS 100 to the ISDN 101, the data undergoes speed conversion (I.460) from 32 Kbps to 64 Kbps by the PHS processor 222, and the converted data is output to the signal lines 229 and 230.

A signal line 231 outputs a 32 Kbps signal received from the PHS processor 222 through a digital wireless link as it is. The signal line 231 is connected to the PIAFS controller 221.

Signal lines 232 and 233 connect analog signals input to and output from the analog switch 216 to PCM codecs 310 and 311 (see Fig. 3) in the PHS processor 222.

A signal line 234 transfers the 8 KHz clock, which is extracted from the ISDN 101 by the digital PLL 235 in the ISDN interface part 219, to the PHS processor 222.

Fig. 3 shows the internal structure of the PHS processor 222 included in the facsimile apparatus FS1 of the first embodiment.

A CPU 301 includes a RAM (not shown) and a ROM (not shown) and performs control operations related to the PHS 100. The CPU 301 is connected to a data bus 302. The CPU

301 performs various control operations described below in accordance with a program stored in its ROM.

A PHS baseband processor 303 assembles and decomposes PHS transmission frames. The PHS baseband processor 303 is capable of processing two slots in a PHS transmission frame.

A radio frequency unit 304 performs frequency conversion of data to be transferred so that the data is transferred at 1.9 GHz band. The radio frequency unit 304 is connected to an antenna 305.

Adaptive differential pulse code modulation (ADPCM)/PCM converters 306 and 307 convert ADPCM-coded audio data at 32 Kbps, which is used in PHS wireless transmission, into PCM-coded audio data at 64 Kbps, which is used by the ISDN 101. The ADPCM/PCM converters 306 and 307 convert PCM-coded audio data at 64 Kbps into ADPCM-coded audio data at 32 Kbps.

I.460 converters 308 and 309 perform speed conversion of 32-Kbps data into 64-Kbps data in order to transmit data, which is transferred using the PHS wireless transmission, to the ISDN 101.

The PCM codecs 310 and 311 converts analog signals input from the analog switch 216 through the signal lines 232 and 233 into PCM-coded data at 64 Kbps.

A switch 312 switches 32-Kbps data output from the PHS baseband processor 303.

A switch 313 connects either of 32-Kbps data on two

channels, which are output from the PHS baseband processor 303, to the PIAFS controller 221.

Switches 314 and 315 switch data to be connected to the signal lines 229 and 230, which are 64-Kbps transmission lines.

Switches 316 and 317 switch between whether to connect data, which is received from the digital wireless link and is PCM-converted, to a bus for transmitting to the ISDN 101 or to a bus for inputting to the PCM codecs 310 and 311 that perform analog conversion.

Switches 318 and 319 switch data received from the ISDN 101 or data received from the digital wireless link to be connected to the PCM codecs 310 and 311.

The switches 312 to 319 are controlled by the CPU 301. The facsimile apparatus FS1 can function both as a master station of the PHS 100 and as a remote station of the wireless switchboard RC1 by means of the switches 316 to 319.

A temperature-compensated crystal oscillator (TCXO) 320 generates a 19.2 MHz clock with an accuracy of  $\pm 3$  ppm irrespective of the temperature. The PHS baseband processor 303 and the radio frequency unit 304 operate based on the clock.

A multiplier circuit 321 generates a 19.2 MHz clock in synchronism with the 8 KHz clock output from the ISDN interface part 219.

Under the control of the CPU 301, a clock selecting switch 322 selects between the clock generated by the TCXO 320 and the clock generated by the multiplier circuit 321 in synchronism with the ISDN 101.

5        Fig. 4 shows a data stream when making a call from the PHS 100 while the facsimile apparatus FS1 of the first embodiment is connected to the ISDN 101.

10       Fig. 5 shows a data stream when performing facsimile communication by the facsimile apparatus FS1 of the first embodiment when the facsimile apparatus FS1 is connected to the ISDN 101.

15       Fig. 6 shows a data stream when performing facsimile communication by the facsimile apparatus FS1 of the first embodiment when the facsimile apparatus FS1 is not connected to the ISDN 101.

20       Fig. 7 shows a sequence when making a call from the PHS 100 through the facsimile apparatus FS1 of the first embodiment while the facsimile apparatus FS1 is connected to the ISDN 101.

25       Fig. 8 shows a sequence when making a call from the facsimile apparatus FS1 of the first embodiment when the facsimile apparatus FS1 is not connected to the ISDN 101.

      The operation in which the facsimile apparatus FS1 and the ISDN 101 are interconnected and the operation in which the facsimile apparatus FS1 is not connected to the ISDN 101

are described next.

Figs. 9 and 10 are flowcharts showing control operations of the facsimile apparatus FS1 of the first embodiment.

5 Operation when facsimile apparatus FS1 is connected to ISDN 101 and functions as master station of PHS 100:

Immediately after turning on the facsimile apparatus FS1, the CPU 201 performs activation control of the layer 1 of the ISDN interface part 219. The ISDN interface part 219 transmits INFO1 signal (asynchronous signal) specified by the ITU-T Recommendations I.430 to the ISDN 101, and starts processing to establish synchronization (S601).

10  
15  
20  
25  
30  
35  
40  
45  
50  
55  
60  
65  
70  
75  
80  
85  
90  
95  
100  
105  
110  
115  
120  
125  
130  
135  
140  
145  
150  
155  
160  
165  
170  
175  
180  
185  
190  
195  
200  
205  
210  
215  
220  
225  
230  
235  
240  
245  
250  
255  
260  
265  
270  
275  
280  
285  
290  
295  
300  
305  
310  
315  
320  
325  
330  
335  
340  
345  
350  
355  
360  
365  
370  
375  
380  
385  
390  
395  
400  
405  
410  
415  
420  
425  
430  
435  
440  
445  
450  
455  
460  
465  
470  
475  
480  
485  
490  
495  
500  
505  
510  
515  
520  
525  
530  
535  
540  
545  
550  
555  
560  
565  
570  
575  
580  
585  
590  
595  
600  
605  
610  
615  
620  
625  
630  
635  
640  
645  
650  
655  
660  
665  
670  
675  
680  
685  
690  
695  
700  
705  
710  
715  
720  
725  
730  
735  
740  
745  
750  
755  
760  
765  
770  
775  
780  
785  
790  
795  
800  
805  
810  
815  
820  
825  
830  
835  
840  
845  
850  
855  
860  
865  
870  
875  
880  
885  
890  
895  
900  
905  
910  
915  
920  
925  
930  
935  
940  
945  
950  
955  
960  
965  
970  
975  
980  
985  
990  
995  
1000  
1005  
1010  
1015  
1020  
1025  
1030  
1035  
1040  
1045  
1050  
1055  
1060  
1065  
1070  
1075  
1080  
1085  
1090  
1095  
1100  
1105  
1110  
1115  
1120  
1125  
1130  
1135  
1140  
1145  
1150  
1155  
1160  
1165  
1170  
1175  
1180  
1185  
1190  
1195  
1200  
1205  
1210  
1215  
1220  
1225  
1230  
1235  
1240  
1245  
1250  
1255  
1260  
1265  
1270  
1275  
1280  
1285  
1290  
1295  
1300  
1305  
1310  
1315  
1320  
1325  
1330  
1335  
1340  
1345  
1350  
1355  
1360  
1365  
1370  
1375  
1380  
1385  
1390  
1395  
1400  
1405  
1410  
1415  
1420  
1425  
1430  
1435  
1440  
1445  
1450  
1455  
1460  
1465  
1470  
1475  
1480  
1485  
1490  
1495  
1500  
1505  
1510  
1515  
1520  
1525  
1530  
1535  
1540  
1545  
1550  
1555  
1560  
1565  
1570  
1575  
1580  
1585  
1590  
1595  
1600  
1605  
1610  
1615  
1620  
1625  
1630  
1635  
1640  
1645  
1650  
1655  
1660  
1665  
1670  
1675  
1680  
1685  
1690  
1695  
1700  
1705  
1710  
1715  
1720  
1725  
1730  
1735  
1740  
1745  
1750  
1755  
1760  
1765  
1770  
1775  
1780  
1785  
1790  
1795  
1800  
1805  
1810  
1815  
1820  
1825  
1830  
1835  
1840  
1845  
1850  
1855  
1860  
1865  
1870  
1875  
1880  
1885  
1890  
1895  
1900  
1905  
1910  
1915  
1920  
1925  
1930  
1935  
1940  
1945  
1950  
1955  
1960  
1965  
1970  
1975  
1980  
1985  
1990  
1995  
2000  
2005  
2010  
2015  
2020  
2025  
2030  
2035  
2040  
2045  
2050  
2055  
2060  
2065  
2070  
2075  
2080  
2085  
2090  
2095  
2100  
2105  
2110  
2115  
2120  
2125  
2130  
2135  
2140  
2145  
2150  
2155  
2160  
2165  
2170  
2175  
2180  
2185  
2190  
2195  
2200  
2205  
2210  
2215  
2220  
2225  
2230  
2235  
2240  
2245  
2250  
2255  
2260  
2265  
2270  
2275  
2280  
2285  
2290  
2295  
2300  
2305  
2310  
2315  
2320  
2325  
2330  
2335  
2340  
2345  
2350  
2355  
2360  
2365  
2370  
2375  
2380  
2385  
2390  
2395  
2400  
2405  
2410  
2415  
2420  
2425  
2430  
2435  
2440  
2445  
2450  
2455  
2460  
2465  
2470  
2475  
2480  
2485  
2490  
2495  
2500  
2505  
2510  
2515  
2520  
2525  
2530  
2535  
2540  
2545  
2550  
2555  
2560  
2565  
2570  
2575  
2580  
2585  
2590  
2595  
2600  
2605  
2610  
2615  
2620  
2625  
2630  
2635  
2640  
2645  
2650  
2655  
2660  
2665  
2670  
2675  
2680  
2685  
2690  
2695  
2700  
2705  
2710  
2715  
2720  
2725  
2730  
2735  
2740  
2745  
2750  
2755  
2760  
2765  
2770  
2775  
2780  
2785  
2790  
2795  
2800  
2805  
2810  
2815  
2820  
2825  
2830  
2835  
2840  
2845  
2850  
2855  
2860  
2865  
2870  
2875  
2880  
2885  
2890  
2895  
2900  
2905  
2910  
2915  
2920  
2925  
2930  
2935  
2940  
2945  
2950  
2955  
2960  
2965  
2970  
2975  
2980  
2985  
2990  
2995  
3000  
3005  
3010  
3015  
3020  
3025  
3030  
3035  
3040  
3045  
3050  
3055  
3060  
3065  
3070  
3075  
3080  
3085  
3090  
3095  
3100  
3105  
3110  
3115  
3120  
3125  
3130  
3135  
3140  
3145  
3150  
3155  
3160  
3165  
3170  
3175  
3180  
3185  
3190  
3195  
3200  
3205  
3210  
3215  
3220  
3225  
3230  
3235  
3240  
3245  
3250  
3255  
3260  
3265  
3270  
3275  
3280  
3285  
3290  
3295  
3300  
3305  
3310  
3315  
3320  
3325  
3330  
3335  
3340  
3345  
3350  
3355  
3360  
3365  
3370  
3375  
3380  
3385  
3390  
3395  
3400  
3405  
3410  
3415  
3420  
3425  
3430  
3435  
3440  
3445  
3450  
3455  
3460  
3465  
3470  
3475  
3480  
3485  
3490  
3495  
3500  
3505  
3510  
3515  
3520  
3525  
3530  
3535  
3540  
3545  
3550  
3555  
3560  
3565  
3570  
3575  
3580  
3585  
3590  
3595  
3600  
3605  
3610  
3615  
3620  
3625  
3630  
3635  
3640  
3645  
3650  
3655  
3660  
3665  
3670  
3675  
3680  
3685  
3690  
3695  
3700  
3705  
3710  
3715  
3720  
3725  
3730  
3735  
3740  
3745  
3750  
3755  
3760  
3765  
3770  
3775  
3780  
3785  
3790  
3795  
3800  
3805  
3810  
3815  
3820  
3825  
3830  
3835  
3840  
3845  
3850  
3855  
3860  
3865  
3870  
3875  
3880  
3885  
3890  
3895  
3900  
3905  
3910  
3915  
3920  
3925  
3930  
3935  
3940  
3945  
3950  
3955  
3960  
3965  
3970  
3975  
3980  
3985  
3990  
3995  
4000  
4005  
4010  
4015  
4020  
4025  
4030  
4035  
4040  
4045  
4050  
4055  
4060  
4065  
4070  
4075  
4080  
4085  
4090  
4095  
4100  
4105  
4110  
4115  
4120  
4125  
4130  
4135  
4140  
4145  
4150  
4155  
4160  
4165  
4170  
4175  
4180  
4185  
4190  
4195  
4200  
4205  
4210  
4215  
4220  
4225  
4230  
4235  
4240  
4245  
4250  
4255  
4260  
4265  
4270  
4275  
4280  
4285  
4290  
4295  
4300  
4305  
4310  
4315  
4320  
4325  
4330  
4335  
4340  
4345  
4350  
4355  
4360  
4365  
4370  
4375  
4380  
4385  
4390  
4395  
4400  
4405  
4410  
4415  
4420  
4425  
4430  
4435  
4440  
4445  
4450  
4455  
4460  
4465  
4470  
4475  
4480  
4485  
4490  
4495  
4500  
4505  
4510  
4515  
4520  
4525  
4530  
4535  
4540  
4545  
4550  
4555  
4560  
4565  
4570  
4575  
4580  
4585  
4590  
4595  
4600  
4605  
4610  
4615  
4620  
4625  
4630  
4635  
4640  
4645  
4650  
4655  
4660  
4665  
4670  
4675  
4680  
4685  
4690  
4695  
4700  
4705  
4710  
4715  
4720  
4725  
4730  
4735  
4740  
4745  
4750  
4755  
4760  
4765  
4770  
4775  
4780  
4785  
4790  
4795  
4800  
4805  
4810  
4815  
4820  
4825  
4830  
4835  
4840  
4845  
4850  
4855  
4860  
4865  
4870  
4875  
4880  
4885  
4890  
4895  
4900  
4905  
4910  
4915  
4920  
4925  
4930  
4935  
4940  
4945  
4950  
4955  
4960  
4965  
4970  
4975  
4980  
4985  
4990  
4995  
5000  
5005  
5010  
5015  
5020  
5025  
5030  
5035  
5040  
5045  
5050  
5055  
5060  
5065  
5070  
5075  
5080  
5085  
5090  
5095  
5100  
5105  
5110  
5115  
5120  
5125  
5130  
5135  
5140  
5145  
5150  
5155  
5160  
5165  
5170  
5175  
5180  
5185  
5190  
5195  
5200  
5205  
5210  
5215  
5220  
5225  
5230  
5235  
5240  
5245  
5250  
5255  
5260  
5265  
5270  
5275  
5280  
5285  
5290  
5295  
5300  
5305  
5310  
5315  
5320  
5325  
5330  
5335  
5340  
5345  
5350  
5355  
5360  
5365  
5370  
5375  
5380  
5385  
5390  
5395  
5400  
5405  
5410  
5415  
5420  
5425  
5430  
5435  
5440  
5445  
5450  
5455  
5460  
5465  
5470  
5475  
5480  
5485  
5490  
5495  
5500  
5505  
5510  
5515  
5520  
5525  
5530  
5535  
5540  
5545  
5550  
5555  
5560  
5565  
5570  
5575  
5580  
5585  
5590  
5595  
5600  
5605  
5610  
5615  
5620  
5625  
5630  
5635  
5640  
5645  
5650  
5655  
5660  
5665  
5670  
5675  
5680  
5685  
5690  
5695  
5700  
5705  
5710  
5715  
5720  
5725  
5730  
5735  
5740  
5745  
5750  
5755  
5760  
5765  
5770  
5775  
5780  
5785  
5790  
5795  
5800  
5805  
5810  
5815  
5820  
5825  
5830  
5835  
5840  
5845  
5850  
5855  
5860  
5865  
5870  
5875  
5880  
5885  
5890  
5895  
5900  
5905  
5910  
5915  
5920  
5925  
5930  
5935  
5940  
5945  
5950  
5955  
5960  
5965  
5970  
5975  
5980  
5985  
5990  
5995  
6000  
6005  
6010  
6015  
6020  
6025  
6030  
6035  
6040  
6045  
6050  
6055  
6060  
6065  
6070  
6075  
6080  
6085  
6090  
6095  
6100  
6105  
6110  
6115  
6120  
6125  
6130  
6135  
6140  
6145  
6150  
6155  
6160  
6165  
6170  
6175  
6180  
6185  
6190  
6195  
6200  
6205  
6210  
6215  
6220  
6225  
6230  
6235  
6240  
6245  
6250  
6255  
6260  
6265  
6270  
6275  
6280  
6285  
6290  
6295  
6300  
6305  
6310  
6315  
6320  
6325  
6330  
6335  
6340  
6345  
6350  
6355  
6360  
6365  
6370  
6375  
6380  
6385  
6390  
6395  
6400  
6405  
6410  
6415  
6420  
6425  
6430  
6435  
6440  
6445  
6450  
6455  
6460  
6465  
6470  
6475  
6480  
6485  
6490  
6495  
6500  
6505  
6510  
6515  
6520  
6525  
6530  
6535  
6540  
6545  
6550  
6555  
6560  
6565  
6570  
6575  
6580  
6585  
6590  
6595  
6600  
6605  
6610  
6615  
6620  
6625  
6630  
6635  
6640  
6645  
6650  
6655  
6660  
6665  
6670  
6675  
6680  
6685  
6690  
6695  
6700  
6705  
6710  
6715  
6720  
6725  
6730  
6735  
6740  
6745  
6750  
6755  
6760  
6765  
6770  
6775  
6780  
6785  
6790  
6795  
6800  
6805  
6810  
6815  
6820  
6825  
6830  
6835  
6840  
6845  
6850  
6855  
6860  
6865  
6870  
6875  
6880  
6885  
6890  
6895  
6900  
6905  
6910  
6915  
6920  
6925  
6930  
6935  
6940  
6945  
6950  
6955  
6960  
6965  
6970  
6975  
6980  
6985  
6990  
6995  
7000  
7005  
7010  
7015  
7020  
7025  
7030  
7035  
7040  
7045  
7050  
7055  
7060  
7065  
7070  
7075  
7080  
7085  
7090  
7095  
7100  
7105  
7110  
7115  
7120  
7125  
7130  
7135  
7140  
7145  
7150  
7155  
7160  
7165  
7170  
7175  
7180  
7185  
7190  
7195  
7200  
7205  
7210  
7215  
7220  
7225  
7230  
7235  
7240  
7245  
7250  
7255  
7260  
7265  
7270  
7275  
7280  
7285  
7290  
7295  
7300  
7305  
7310  
7315  
7320  
7325  
7330  
7335  
7340  
7345  
7350  
7355  
7360  
7365  
7370  
7375  
7380  
7385  
7390  
7395  
7400  
7405  
7410  
7415  
7420  
7425  
7430  
7435  
7440  
7445  
7450  
7455  
7460  
7465  
7470  
7475  
7480  
7485  
7490  
7495  
7500  
7505  
7510  
7515  
7520  
7525  
7530  
7535  
7540  
7545  
7550  
7555  
7560  
7565  
7570  
7575  
7580  
7585  
7590  
7595  
7600  
7605  
7610  
7615  
7620  
7625  
7630  
7635  
7640  
7645  
7650  
7655  
7660  
7665  
7670  
7675  
7680  
7685  
7690  
7695  
7700  
7705  
7710  
7715  
7720  
7725  
7730  
7735  
7740  
7745  
7750  
7755  
7760  
7765  
7770  
7775  
7780  
7785  
7790  
7795  
7800  
7805  
7810  
7815  
7820  
7825  
7830  
7835  
7840  
7845  
7850  
7855  
7860  
7865  
7870  
7875  
7880  
7885  
7890  
7895  
7900  
7905  
7910  
7915  
7920  
7925  
7930  
7935  
7940  
7945  
7950  
7955  
7960  
7965  
7970  
7975  
7980  
7985  
7990  
7995  
8000  
8005  
8010  
8015  
8020  
8025  
8030  
8035  
8040  
8045  
8050  
8055  
8060  
8065  
8070  
8075  
8080  
8085  
8090  
8095  
8100  
8105  
8110  
8115  
8120  
8125  
8130  
8135  
8140  
8145  
8150  
8155  
8160  
8165  
8170  
8175  
8180  
8185  
8190  
8195  
8200  
8205  
8210  
8215  
8220  
8225  
8230  
8235  
8240  
8245  
8250  
8255  
8260  
8265  
8270  
8275  
8280  
8285  
8290  
8295  
8300  
8305  
8310  
8315  
8320  
8325  
8330  
8335  
8340  
8345  
8350  
8355  
8360  
8365  
8370  
8375  
8380  
8385  
8390  
8395  
8400  
8405  
8410  
8415  
8420  
8425  
8430  
8435  
8440  
8445  
8450  
8455  
8460  
8465  
8470  
8475  
8480  
8485  
8490  
8495  
8500  
8505  
8510  
8515  
8520  
8525  
8530  
8535  
8540  
8545  
8550  
8555  
8560  
8565  
8570  
8575  
8580  
8585  
8590  
8595  
8600  
8605  
8610  
8615  
8620  
8625  
8630  
8635  
8640  
8645  
8650  
8655  
8660  
8665  
8670  
8675  
8680  
8685  
8690  
8695  
8700  
8705  
8710  
8715  
8720  
8725  
8730  
8735  
8740  
8745  
8750  
8755  
8760  
8765  
8770  
8775  
8780  
8785  
8790  
8795  
8800  
8805  
8810  
8815  
8820  
8825  
8830  
8835  
8840  
8845  
8850  
8855  
8860  
8865  
8870  
8875  
8880  
8885  
8890  
8895  
8900  
8905  
8910  
8915  
8920  
8925  
8930  
8935  
8940  
8945  
8950  
8955  
8960  
8965  
8970  
8975  
8980  
8985  
8990  
8995  
9000  
9005  
9010  
9015  
9020  
9025  
9030  
9035  
9040  
9045  
9050  
9055  
9060  
9065  
9070  
9075  
9080  
9085  
9090  
9095  
9100  
9105  
9110  
9115  
9120  
9125  
9130  
9135  
9140  
9145  
9150  
9155  
9160  
9165  
9170  
9175  
9180  
9185  
9190  
9195  
9200  
9205  
9210  
9215  
9220  
9225  
9230  
9235  
9240  
9245  
9250  
9255  
9260  
9265  
9270  
9275  
9280  
9285  
9290  
9295  
9300  
9305  
9310  
9315  
9320  
9325  
9330  
9335  
9340  
9345  
9350  
9355  
9360  
9365  
9370  
9375  
9380  
9385  
9390  
9395  
9400  
9405  
9410  
9415  
9420  
9425  
9430  
9435  
9440  
9445  
9450  
9455  
9460  
9465  
9470  
9475  
9480  
9485  
9490  
9495  
9500  
9505  
9510  
9515  
9520  
9525  
9530  
9535  
9540  
9545  
9550  
9555  
9560  
9565  
9570  
9575  
9580  
9585  
9590  
9595  
9600  
9605  
9610  
9615  
9620  
9625  
9630  
9635  
9640  
9645  
9650  
9655  
9660  
9665  
9670  
9675  
9680  
9685  
9690  
9695  
9700  
9705  
9710  
9715  
9720  
9725  
9730  
9735  
9740  
9745  
9750  
9755  
9760  
9765  
9770  
9775  
9780  
9785  
9790  
9795  
9800  
9805  
9810  
9815  
9820  
9825  
9830  
9835  
9840  
9845  
9850  
9855  
9860  
9865  
9870  
9875  
9880  
9885  
9890  
9895  
9900  
9905  
9910  
9915  
9920  
9925  
9930  
9935  
9940  
9945  
9950  
9955  
9960  
9965  
9970  
9975  
9980  
9985  
9990  
9995  
10000  
10005  
10010  
10015  
10020  
10025  
10030  
10035  
10040  
10045  
10050  
10055  
10060  
10065  
10070  
10075  
10080  
10085  
10090  
10095  
10100  
10105  
10110  
10115  
10120  
10125  
10130  
10135  
10140  
10145  
10150  
10155  
10160  
10165  
10170  
10175  
10180  
10185

(S604). At this stage, the CPU 201 determines that connection has been made to the ISDN 101.

When the CPU 201 determines that connection has been made to the ISDN 101, it is determined that the facsimile apparatus FS1 operates as a master station of the PHS 100. The CPU 201 displays, on the display unit 236, "connected to ISDN 101", "operating as master station of PHS 100", and the like. The CPU 201 then instructs the CPU 301 of the PHS processor 222 to operate as a master station of the PHS 100 (S605).

In response to the instruction, the CPU 301 controls the switches 316 to 319 (S606). Specifically, the digital signal side of the PCM codecs 310 and 311 is connected to the ISDN 101 (signal lines 229 and 230). In other words, the switch 316 is switched to interconnect the switch 314 and the signal line 229. The switch 317 is switched to interconnect the switch 315 and the signal line 230. The switch 318 is switched to interconnect the switch 314 and the PCM codec 310. The switch 319 is switched to interconnect the switch 315 and the PCM codec 311.

The CPU 301 controls the clock selecting switch 322 to select a clock multiplied by the multiplier circuit 321 as a clock to be used for performing digital wireless communication (S607). Accordingly, data transmission and reception in network synchronization can be performed, and



data underflow and overflow are prevented.

The digital wireless communication protocol processing starts up only a master station processing facility for the PHS 100 (S608).

5       The operation for making a call from the PHS 100 to the ISDN 101 through the facsimile apparatus FS1 and talking to a person connected through the ISDN 101 is described next.

10       When a call is dialed from the PHS 100, the PHS 100 performs outgoing call processing. The PHS 100 transmits a link channel establishment request to the facsimile apparatus FS1. From this time onward, the facsimile apparatus FS1 establishes a digital wireless link with the PHS 100 in accordance with the sequence shown in Fig. 7.

15       When the CPU 301 in the facsimile apparatus FS1 receives a call setup message and subsequent additional information from the PHS 100 (S609), the CPU 301 informs the CPU 201 of the received message and the information (S610). The CPU 201 instructs the ISDN interface part 219 to transmit the call setup message to the ISDN 101 (S611). In response to a response from the ISDN 101 (S612), the ISDN interface part 219 informs the CPU 201 of the reception of the response. The CPU 201 informs the CPU 301 of the response. The CPU 301 transmits the response message to the PHS 100 (S613).

25       From this step onward, B-channel data can be

transmitted and received between the facsimile apparatus FS1 and the destination terminal FS2 through the ISDN 101.

Specifically, audio data transmitted from the PHS 100 is transmitted to the ISDN 101 by the facsimile apparatus FS1, whereas audio data received from the ISDN 101 is transmitted to the PHS 100 by the facsimile apparatus FS1.

Fig. 4 shows the data flow in the above example.

Specifically, audio data received from the PHS 100 through the antenna 305 and the radio frequency unit 304 is converted into a baseband digital signal by the PHS baseband processor 303. Under the control of the CPU 301, the switch 312 is configured to interconnect the PHS baseband processor 303 and the ADPCM/PCM converter 306. The ADPCM/PCM converter 306 converts the ADPCM audio data received from the PHS 100 into 64-Kbps PCM-coded data (S614), and the data is transferred to the ISDN 101 through the switches 314 and 316 (S615).

When the facsimile apparatus FS1 is operating as a master station of the PHS 100, and when a facsimile transmission request is made in the facsimile apparatus FS1 (S616), the CPU 206 informs the CPU 201 of the facsimile transmission request (S617). Under the control of the informed CPU 201 that has been informed of the request, a call setup message is transmitted to the ISDN 101 (S618). When a response message from the ISDN 101 is received (S619),

the analog switch 216 is switched (S620), and the CPU 206 is instructed to start performing facsimile transmission.

In response to the instruction, the CPU 206 causes the color printer/color scanner 210 to read image data. The read image data is compressed, and the compressed data is modulated by the facsimile modem 212 (S621). The modulated analog signal is input to the PCM codec 310 via the analog switch 216, and the PCM codec 310 performs PCM code conversion of the signal (S622). The PCM-coded data is input to the ISDN 101 through the switches 318, 314, and 316 (S623).

Fig. 5 shows the data flow in the above example. Operation when facsimile apparatus FS1 is not connected to ISDN 101 and functions as remote station of wireless switchboard RC1:

In contrast, in step S602, when the layer 1 is not established within a predetermined period of time, the ISDN interface part 219 interrupts the CPU 201, and the CPU 201 determines that no connection has been made to the ISDN 101. When the CPU 201 determines that no connection has been made to the ISDN 101, the CPU 201 displays, on the display unit 236, "not connected to ISDN 101", "operating as remote station of wireless switchboard RC1", and the like. At the same time, the CPU 201 instructs the PHS processor 222 that the facsimile apparatus FS1 should operate as a remote

station digital wireless facsimile apparatus.

When the layer 2 is not established in step S604, the CPU 201 determines that no connection has been made to the ISDN 101, and displays the same messages.

5 Referring to Fig. 10, the CPU 201 displays, on the display unit 236, "not connected to ISDN 101", "operating as remote station of wireless switchboard RC1", and the like. The CPU 201 instructs the CPU 301 of the PHS processor 222 that the facsimile apparatus FS1 should operate as a remote station of the wireless switchboard RC1 (S624).

10 In response to the instruction, the CPU 301 controls the switches 316 to 319 (S625). Specifically, the digital signal side of the PCM codec 310 is connected to the ADPCM/PCM converter 306 via the switches 318, 316, and 314. Also, the digital signal side of the PCM codec 311 is connected to the ADPCM/PCM converter 307 via the switches 15 319, 317, and 315.

20 The CPU 301 controls the clock selecting switch 322 to select the clock generated by the TCXO 320 as the clock used for performing digital wireless communication (S626). The reason for this is as follows. Since the degree of accuracy is low of a free-running frequency of the digital PLL 235 that extracts the clock from the ISDN 101, the frequency accuracy required for performing digital wireless 25 communication cannot be obtained when the ISDN 101 is not

connected.

Even when the ISDN 101 is not connected, provision of a highly accurate digital PLL in the ISDN interface part 219 enables the free-running clock of the digital PLL to be used  
5 as a digital wireless communication clock.

The digital wireless communication protocol processing starts up only a remote station processing facility for the wireless switchboard RC1 (S627).

Next, the operation for performing facsimile transmission by the facsimile apparatus FS1 as a remote station of the wireless switchboard RC1 is described.

When a facsimile transmission request is input from the operation panel 211 (S628), the CPU 206 recognizes the input dial information and informs the CPU 201 of the facsimile transmission request and the dial information (S629). The CPU 201 instructs the CPU 301 of the PHS processor 222 to perform facsimile transmission, and the CPU 301 starts processing to establish a wireless link for the facsimile transmission (S630).

Specifically, the facsimile apparatus FS1 transmits a link channel establishment request to the wireless switchboard RC1. From this step onward, the facsimile apparatus FS1 establishes a digital wireless link with the wireless switchboard RC1 and transmits a transmission  
20 request to the wireless switchboard RC1 in accordance with  
25

the sequence shown in Fig. 8.

When a response message in response to the facsimile transmission request is received from the wireless switchboard RC1 (S631), the facsimile apparatus FS1 enters a state in which connection has been made to the ISDN 101 through the digital wireless link and the wireless switchboard RC1. The CPU 301 informs the CPU 201 of the response, and the CPU 201 switches the analog switch 216 (S632). Subsequently, the CPU 206 is instructed to start the facsimile transmission (S633). In response to the instruction, the CPU 206 activates the color printer/color scanner 210 to read image data. The read image data is compressed, and the compressed data is input to the facsimile modem 212 (S634).

The facsimile modem 212 modulates the input data into an analog signal, and the converted analog signal is input to the analog switch 216. Since the analog switch 216 is connected to the PCM codec 310, the analog signal input from the analog switch 216 to the PCM codec 310 is converted to 64-Kbps PCM-coded data (S635), and the converted data is input to the ADPCM/PCM converter 306 via the switches 318, 316, and 314. The input signal is converted from the 64-Kbps PCM data into 32-Kbps ADPCM data (S636) and is input to the PHS baseband processor 303 via the switch 312.

The signal input to the PHS baseband processor 303 is

assembled into a PHS transmission frame by the PHS baseband processor 303 (S637). Subsequently, the radio frequency unit 304 modulates the PHS transmission frame, and the modulated frame is transmitted to the wireless switchboard RC1. The wireless switchboard RC1 transmits the frame to the ISDN 101 (S638).

The facsimile transmission is as described above.

Next, the operation of audio communication using the handset 213 is described.

In response to an outgoing call request from the handset (S639), the CPU 206 informs the CPU 201 of the outgoing call request (S640). In response to the request, the CPU 201 instructs the CPU 301 to place the outgoing call by establishing a digital wireless link and by instructing the wireless switchboard RC1 to transfer the call (S641). When a response from the wireless switchboard RC1 is made in response to the outgoing call request (S642), the CPU 201 switches the analog switch 216 (S643). The CPU 201 causes an analog audio signal input from the handset 213 to be input to the PCM codec 310 (S644). The processing from this step onward is the same as the processing from step S635 onward when performing the facsimile transmission.

As described above, the data bus and the wireless protocol processing are switched depending on whether the facsimile apparatus FS1 is connected to the ISDN 101. This

enables the facsimile apparatus FS1 to be automatically switched between operating as a master station of the PHS 100 and a remote station of the wireless switchboard RC1.

According to the first embodiment, the most appropriate communication mode is automatically set in accordance with the location at which the facsimile apparatus FS1 is used.

According to the first embodiment, provision of the TCXO 320 for generating a clock to be used for performing intercommunication between the facsimile apparatus FS1 and the wireless switchboard RC1 enables the facsimile apparatus FS1 to perform digital wireless communication at a predetermined frequency with predetermined accuracy even when operating as a master station of the PHS 100 or a remote station of the wireless switchboard RC1.

According to the first embodiment, when the facsimile apparatus FS1 is connected to the ISDN 101, the master station digital wireless communication protocol for the PHS 100 is selected. When the facsimile apparatus FS1 is not connected to the ISDN 101, the remote station digital wireless communication protocol for the wireless switchboard RC1 is selected. Hence, the operation of the facsimile apparatus FS1 between the master station operation and the remote station operation is switched only by software control.

According to the first embodiment, the connection state



of the facsimile apparatus FS1 to the ISDN 101 is displayed, enabling a user to clearly understand the communication state of the facsimile apparatus FS1.

According to the first embodiment, provision of the switches 316 and 317, which are inserted between the ADPCM/PCM converters 306 and 307 and the ISDN 101, and the switches 318 and 319, which are inserted between the ADPCM/PCM converters 306 and 307 and the PCM codecs 310 and 311, enables the facsimile apparatus FS1 to use the same circuit when operating as a master station of the PHS 100 and a remote station of the wireless switchboard RC1.

#### SECOND EMBODIMENT

In the first embodiment, the facsimile apparatus FS1 determines the state of the connection with the ISDN 101 only when the facsimile apparatus FS1 is turned on. According to a second embodiment of the present invention, the facsimile apparatus FS1 continuously or periodically determines the state of the connection with the ISDN 101.

If the state of the connection with the ISDN 101 changes, the PHS processor 222 is initialized, and the communication setting is performed in accordance with the state of the connection.

According to the second embodiment, when the state of the connection of the facsimile apparatus FS1 with the ISDN 101 changes after the facsimile apparatus FS1 has been

turned on, the facsimile apparatus FS1 can be continuously used without first turning off and again turning on the facsimile apparatus FS1.

#### THIRD EMBODIMENT

5           In the first embodiment, the facsimile apparatus FS1 has the PHS processor 222 including therein the TCXO 320 and the multiplier circuit 321. In accordance with the communication mode, one of the 19.2 MHz clocks generated by the TCXO 320 and the multiplier circuit 321 is selected to be used for performing communication. According to a third embodiment of the present invention, the TCXO 320 and the multiplier circuit 321 are provided in a region other than that specified in the first embodiment. For example, a digital PLL in an ISDN interface part is operated by a TCXO with a high frequency accuracy, and a clock supplied from the ISDN interface part is always used in a PHS processor.

#### FOURTH EMBODIMENT

10           In the first embodiment, the PHS system is used as the wireless link system, and the ISDN is used as the wired communication line. According to a fourth embodiment of the present invention, other wireless communication systems such as the Digital European Cordless Telephone (DECT) system, the Cordless Telephony Generation 2 (CT2) for England, or the Cordless Telephony Generation 3 (CT3) for Sweden, the  
20           Universal Digital Portable Communications (UDPC), or  
25

cellular phone systems such as the Personal Digital Cellular (PDC) system, the Global System for Mobile Communications (GSM), the Code Division Multiple Access (CDMA)-One, or the International Mobile Telecommunication 2000 (IMT2000) can be used. Also other wired communication lines such as analog public lines or other digital lines can be used.

In the case of using an analog public line as the wired communication line, the state of the connection with the analog public line is determined by whether the value of the current flowing when the loop is closed is equal to or greater than a predetermined value.

When the analog public line is used as the wired communication line, the digital wireless communication processing is not required to operate in synchronism with the analog public communication line. Therefore, the multiplier circuit 321 and the clock selecting switch 322 in the PHS processor 222 become unnecessary.

According to the fourth embodiment, when the analog public line is used as the wired communication line, the same advantages as in the first embodiment can be achieved without provision of the multiplier circuit 321 and the clock selecting switch 322 in the PHS processor 222.

Although the facsimile apparatus is described by way of example in the above embodiments, the present invention can be applied to a communication apparatus such as a telephone

or a personal computer having a wired communication function and a wireless communication function.

According to the present invention, the most appropriate communication mode is automatically set in accordance with the location at which a communication apparatus having a wired communication function and a wireless communication function is used. In addition, various advantages as described in the embodiments can be achieved.

While the present invention has been described with reference to what are presently considered to be the preferred embodiments, it is to be understood that the invention is not limited to the disclosed embodiments. On the contrary, the invention is intended to cover various modifications and equivalent arrangements included within the spirit and scope of the appended claims. The scope of the following claims is to be accorded the broadest interpretation so as to encompass all such modifications and equivalent structures and functions.